

An efficient algorithm for solving linear equality-constrained LQR problems

João Sousa-Pinto, Dominique Orban

Abstract—We present a new algorithm for solving linear-quadratic regulator (LQR) problems with linear equality constraints, also known as constrained LQR (CLQR) problems.

Our method’s sequential runtime is linear in the number of stages and constraints, and its parallel runtime is logarithmic in the number of stages.

The main technical contribution of this paper is the derivation of parallelizable techniques for eliminating the linear equality constraints while preserving the standard positive (semi-)definiteness requirements of LQR problems.

Index Terms—Optimal Control, Trajectory Optimization, Parallel Algorithms, Linear Algebra, Functional Programming

I. INTRODUCTION

A. Constrained LQR

Linear-quadratic regulator problems with stagewise linear equality constraints, which we will henceforth refer to as constrained LQR problems, are optimization problems of the form

$$\begin{aligned} \min_{x_0, u_0, \dots, x_N} \quad & \sum_{i=0}^{N-1} \left(\frac{1}{2} x_i^T Q_i x_i + \frac{1}{2} u_i^T R_i u_i + x_i^T M_i u_i \right. \\ & \left. + q_i^T x_i + r_i^T u_i \right) + \frac{1}{2} x_N^T Q_N x_N + q_N^T x_N \\ \text{s.t.} \quad & x_0 = s_0 \text{ and } E_N x_N + e_N = 0 \text{ and} \\ & \forall i \in \{0, \dots, N-1\} \\ & x_{i+1} = A_i x_i + B_i u_i + c_i \\ & C_i x_i + D_i u_i + d_i = 0 \\ & E_i x_i + e_i = 0. \end{aligned} \quad (1)$$

The matrices R_i are all required to be positive definite. Moreover, $Q_i - M_i R_i^{-1} M_i^T$ is always required to be positive semi-definite; equivalently, $\begin{pmatrix} Q_i & M_i \\ M_i^T & R_i \end{pmatrix}$ is required to be positive semi-definite. Without loss of generality, we assume that all R_i and Q_i are symmetric.

Note that these regularity conditions ensure that, even in the unconstrained case, a minimum does indeed exist.

The variables x_i are referred to as the states, and the variables u_i are referred to as the controls. The number of stages is represented as N . The constraints $x_{i+1} = A_i x_i + B_i u_i + c_i$ are

called the dynamics. All remaining equality constraints may or not be present at each stage.

We use n_i and m_i to represent the state and control dimensions at stage i respectively. We use n and m to denote the maximum values of the different n_i and m_i respectively. We use s_i to denote the number of rows of E_i (i.e. the number of state-only equality constraints at stage i) and t_i to denote the number of rows of C_i (i.e. the number of mixed state-and-control equality constraints at stage i). We also use s to represent the total number of state-only equality constraints (i.e. the sum of all s_i) and t to represent the total number of mixed state-and-control equality constraints (i.e. the sum of all t_i).

B. Background

Discrete-time optimal control problems are ubiquitous in the fields of robotics, motion planning, and control theory, often being solved at high frequencies as part of real-time systems.

A key requirement for a solution mechanism to be practical is that it should depend only linearly on the number of stages of the problem (i.e. its planning horizon).

In the case of unconstrained problems, this is typically achieved by either resorting to domain-specific optimization algorithms (such as DDP [1]), or by exploring the sparsity structure of the Newton-KKT system to reduce it to an equivalent LQR problem (as in Stagewise Newton [2] or Primal-Dual iLQR [3]).

When there are constraints present, these are typically handled via either an interior point method (IPM), an augmented Lagrangian (AL) method, or a sequential quadratic programming method (SQP).

When an AL method is chosen, the resulting LQR subproblem will be unconstrained. However, this comes at the cost of losing local superlinear convergence. When an IPM method is used, the resulting LQR subproblem will be constrained only when equality constraints are present (as described in [4] and [5]). When an SQP method is chosen, the resulting LQR subproblem will inherit the linearized constraints of the original subproblem (both equality and inequality); when inequality constraints are present, and as opposed to AL and IPM methods, this subproblem needs to be solved iteratively, and the subsubproblems are constrained LQR problems.

Clearly, constrained LQR problems are of paramount practical importance.

C. Related Work

The first algorithm for solving constrained LQR problems with runtime linear in the number of stages was introduced

in [6]. Prior to that, [7] had presented a method with runtime linear in the number of mixed state-and-control constraints but cubic in the number of state-only constraints.

The algorithm introduced in [8] also has a worst-case runtime linear in the number of stages, but performs only an approximate solution, although requiring weaker positive (semi-)definiteness requirements.

II. RESULTS

We present a new parallelizable algorithm for efficiently solving constrained LQR problems.

Our method consists of the following steps:

- 1) Reduce to an instance where the D_i matrices have full row rank.
- 2) Reduce to an instance where the D_i are of the form $(G_i \ I)$ or simply I .
- 3) Eliminate the $C_i x_i + D_i u_i + d_i = 0$ constraints (also eliminates some of the control variables).
- 4) Eliminate stage $i + 1$ whenever $B_i = 0$.
- 5) Reduce to an instance where the E_i matrices have full row rank.
- 6) Reduce to an instance where the E_i are of the form $(F_i \ I)$ or simply I .
- 7) Eliminate the $E_i x_i + e_i = 0$ constraints (also eliminates some state variables).
- 8) Eliminate stage $i + 1$ whenever $B_i = 0$ (again).
- 9) Solve the resulting unconstrained LQR problem.
- 10) Retrieve the eliminated state and control variables.

All steps of this reduction can be performed in constant parallel runtime with respect to the number of stages, apart from item 4 and item 8, which can be completed in parallel runtime logarithmic in the number of stages.

After this process, we will either have declared infeasibility, or constructed an unconstrained LQR problem whose solution can be traced back to the solution of the original constrained problem.

Note that only the sequential runtimes of item 1 and item 5 depend on s and t , as the number of mixed state-and-control and state-only constraints at each stage will be upper bounded by m_i and n_i respectively afterwards. However, none of the parallel runtimes depend on s or t .

Moreover, note that item 7 may add new mixed state-and-control linear equality constraints (as many as the number of eliminated state variables), forcing us to restart from the first step on the reduced problem (which will have fewer state variables).

Note that item 4 and item 8 can safely be skipped in the sequential version of our algorithm, provided the reductions are applied in decreasing order of stages. This step aims to ensure that the sequence of reductions listed above never has to be run more than $n + 1$ times when each stage is processed in parallel. Without it, the presence of a final-state constraint could cause $N + 1$ steps to be required. This would happen, for example, if all B_i are zero and all A_i are invertible.

A. Reduction to full row rank D_i

Whenever one of the D_i matrices does not have full row rank, we can pick a non-zero vector v such that $v^T D_i = 0$ and

replace any of the constraints in $C_i x_i + D_i u_i + d_i = 0$ corresponding to an index with a non-zero value in v with a new constraint in $E_i x_i + e_i = 0$, specifically $v^T (C_i x_i + d_i) = 0$; this can be iteratively repeated until the D_i is either empty or has full row rank. This can be achieved in sequential runtime $O(t_i m_i^2 (m_i + n_i))$, as only the first $m_i + 1$ rows of C_i need to be considered at each iteration to find such a vector v . This can also be achieved in parallel runtime $O(\log^2 m_i)$, given that each set of $m_i + 1$ rows can be processed in parallel, and that $k \times k$ linear systems can be solved in $O(\log^2 k)$ parallel runtime, as shown in [10].

B. Reduction $D_i = (G_i \ I)$ or $D_i = I$

If D_i is a square matrix, and given that it has full row rank, it must also be invertible. Therefore, we can left-multiply $C_i x_i + D_i u_i + d_i = 0$ by D_i^{-1} to get $(D_i^{-1} C_i) x_i + I_{m_i} u_i + (D_i^{-1} d_i) = 0$.

In this case, it suffices to take:

$$\begin{aligned} C'_i &= D_i^{-1} C_i \\ D'_i &= I_{m_i} \\ d'_i &= D_i^{-1} d_i \end{aligned} \quad (2)$$

The remaining components of the problem are left unmodified.

If D_i is not a square matrix, since each D_i has full row rank, and given that row and column ranks must match (due to the fundamental theorem of linear algebra), we can find invertible matrices L_i and permutation matrices P_i such that $L_i D_i P_i^{-1} = (G_i \ I_{k_i})$, where k_i is number of rows of D_i .

Left-multiplying $C_i x_i + D_i u_i + d_i = 0$ by L_i , we get:

$$\begin{aligned} C_i x_i + D_i u_i + d_i &= 0 \Leftrightarrow \\ (L_i C_i) x_i + (L_i D_i P_i^{-1})(P_i u_i) + (L_i d_i) &= 0. \end{aligned} \quad (3)$$

Letting $v_i = P_i u_i$, we can reformulate the terms appearing in the problem to be written as a function of v_i instead of u_i .

$$\begin{aligned} u_i^T R_i u_i &= (P_i u_i)^T ((P_i^{-1})^T R_i P_i^{-1}) (P_i u_i) \\ &= v_i^T ((P_i^{-1})^T R_i P_i^{-1}) v_i \end{aligned} \quad (4)$$

$$r_i^T u_i = r_i^T P_i^{-1} (P_i u_i) = ((P_i^{-1})^T r_i)^T v_i \quad (5)$$

$$x_i^T M_i u_i = x_i^T (M_i P_i^{-1}) (P_i u_i) = x_i^T (M_i P_i^{-1}) v_i \quad (6)$$

$$\begin{aligned} x_{i+1} &= A_i x_i + B_i u_i + c_i \\ &= A_i x_i + (B_i P_i^{-1})(P_i u_i) + c_i \\ &= A_i x_i + (B_i P_i^{-1})(v_i) + c_i \end{aligned} \quad (7)$$

Therefore, it suffices to take

$$\begin{aligned}
R'_i &= (P_i^{-1})^T R_i P_i^{-1} \\
Q'_i &= Q_i \\
M'_i &= M_i P_i^{-1} \\
A'_i &= A_i \\
B'_i &= B_i P_i^{-1} \\
q'_i &= q_i \\
r'_i &= (P_i^{-1})^T r_i \\
c'_i &= c_i \\
E'_i &= E_i \\
e'_i &= e_i \\
C'_i &= L_i C_i \\
D'_i &= L_i D_i P_i^{-1} = (G_i \quad I_{k_i}) \\
d'_i &= L_i d_i.
\end{aligned} \tag{8}$$

C. Eliminating $C_i x_i + D_i u_i + d_i = 0$

Due to prior reductions, there are two cases to consider: if D_i is a square matrix, then $D_i = I_m$; otherwise, $D_i = (G_i \quad I_m)$.

If $D_i = I_m$, $C_i x_i + D_i u_i + d_i = 0 \Leftrightarrow u_i = -C_i x_i - d_i$. We can use this to eliminate the u_i variables. Let's see how this affects the problem formulation:

$$\begin{aligned}
u_i^T R_i u_i &= -(C_i x_i + d_i)^T R_i (-C_i x_i + d_i) \\
&= x_i^T (C_i^T R_i C_i) x_i + 2(C_i^T R_i d_i)^T x_i + d_i^T R_i d_i
\end{aligned} \tag{9}$$

$$\begin{aligned}
x_i^T M_i u_i &= x_i^T M_i (-C_i x_i + d_i) \\
&= x_i^T (-M_i C_i) x_i - (M_i d_i)^T x_i
\end{aligned} \tag{10}$$

$$r_i^T u_i = -r_i^T (C_i x_i + d_i) = -(C_i^T r_i)^T x_i - r_i^T d_i \tag{11}$$

$$\begin{aligned}
x_{i+1} &= A_i x_i + B_i u_i + c_i \\
&= A_i x_i - B_i (C_i x_i + d_i) + c_i \\
&= (A_i - B_i C_i) x_i + (c_i - B_i d_i)
\end{aligned} \tag{12}$$

We can then take

$$\begin{aligned}
R'_i &= I \\
Q'_i &= Q_i + C_i^T R_i C_i - M_i C_i \\
M'_i &= 0 \\
A'_i &= A_i - B_i C_i \\
B'_i &= 0 \\
q'_i &= q_i + 2C_i^T R_i d_i - M_i d_i - C_i^T r_i \\
r'_i &= 0 \\
c'_i &= c_i - B_i d_i \\
E'_i &= E_i \\
e'_i &= e_i.
\end{aligned} \tag{13}$$

Noting that

$$Q'_i = (I \quad -C_i^T) \begin{pmatrix} Q_i & M_i \\ M_i^T & R_i \end{pmatrix} \begin{pmatrix} I \\ -C_i \end{pmatrix}, \tag{14}$$

the positive (semi-)definiteness requirements are clearly preserved.

If D_i is not a square matrix, due to prior reductions, we know that $D_i = (G_i \quad I_{k_i})$, where k_i denotes the number of rows of D_i . In this case, $C_i x_i + D_i u_i + d_i = 0 \Leftrightarrow ((u_i)_j)_{j=k_i+1}^{m_i} = -C_i x_i - G_i ((u_i)_j)_{j=1}^{k_i} - d_i$.

Letting $v_i = ((u_i)_j)_{j=1}^{k_i}$, we can eliminate the $((u_i)_j)_{j=k_i+1}^{m_i}$ variables together with the $C_i x_i + D_i u_i + d_i = 0$ constraints by re-writing the problem in terms of the v_i instead of the u_i .

Writing R_i as $\begin{pmatrix} R_i^{(1)} & R_i^{(2)} \\ (R_i^{(2)})^T & R_i^{(3)} \end{pmatrix}$, where $R_i^{(1)}$ has k_i rows and k_i columns, it holds that

$$\begin{aligned}
u_i^T R_i u_i &= (((u_i)_j)_{j=1}^{k_i})^T R_i^{(1)} ((u_i)_j)_{j=1}^{k_i} \\
&\quad + 2(((u_i)_j)_{j=1}^{k_i})^T R_i^{(2)} (u_i)_{i=k_i+1}^{m_i} \\
&\quad + ((u_i)_{i=k_i+1}^{m_i})^T R_i^{(3)} (u_i)_{i=k_i+1}^{m_i}.
\end{aligned} \tag{15}$$

Note that

$$(((u_i)_j)_{j=1}^{k_i})^T R_i^{(1)} ((u_i)_j)_{j=1}^{k_i} = v_i^T R_i^{(1)} v_i. \tag{16}$$

Moreover,

$$\begin{aligned}
&2(((u_i)_j)_{j=1}^{k_i})^T R_i^{(2)} (u_i)_{i=k_i+1}^{m_i} \\
&= 2v_i^T R_i^{(2)} (-C_i x_i - G_i v_i - d_i) \\
&= -2v_i^T (R_i^{(2)} G_i) v_i - 2x_i^T (C_i^T R_i^{(2)}) v_i - 2d_i^T v_i.
\end{aligned} \tag{17}$$

Also,

$$\begin{aligned}
&(((u_i)_j)_{j=k_i+1}^{m_i})^T R_i^{(3)} (u_i)_{i=k_i+1}^{m_i} \\
&= (-C_i x_i - G_i v_i - d_i)^T R_i^{(3)} (-C_i x_i - G_i v_i - d_i) \\
&= x_i^T (C_i^T R_i^{(3)} C_i) x_i + v_i^T (G_i^T R_i^{(3)} G_i) v_i + 2x_i^T (C_i^T R_i^{(3)} G_i) v_i \\
&\quad + 2(C_i^T R_i^{(3)} d_i)^T x_i + 2(G_i^T R_i^{(3)} d_i)^T v_i + d_i^T R_i^{(3)} d_i.
\end{aligned} \tag{18}$$

Writing M_i as

$$\begin{pmatrix} M_i^{(1)} & M_i^{(2)} \end{pmatrix}, \tag{19}$$

where $M_i^{(1)}$ has k_i columns, it holds that

$$\begin{aligned}
x_i^T M_i u_i &= x_i^T M_i^{(1)} ((u_i)_j)_{j=1}^{k_i} + x_i^T M_i^{(2)} ((u_i)_j)_{j=k_i+1}^{m_i} \\
&= x_i^T M_i^{(1)} v_i + x_i^T M_i^{(2)} (-C_i x_i - G_i v_i - d_i) \\
&= x_i^T (M_i^{(1)} - M_i^{(2)} G_i) v_i - x_i^T (M_i^{(2)} C_i) x_i - (M_i^{(2)} d_i)^T x_i.
\end{aligned} \tag{20}$$

Also, writing r_i as $\begin{pmatrix} r_i^{(1)} \\ r_i^{(2)} \end{pmatrix}$, where $r_i^{(1)}$ has k_i rows, we get

$$\begin{aligned}
r_i^T u_i &= (r_i^{(1)})^T ((u_i)_j)_{j=1}^{k_i} + (r_i^{(2)})^T ((u_i)_j)_{j=k_i+1}^{m_i} \\
&= (r_i^{(1)})^T v_i + (r_i^{(2)})^T (-C_i x_i - G_i v_i - d_i) \\
&= -(C_i^T r_i^{(2)})^T x_i + (r_i^{(1)} - G_i^T r_i^{(2)})^T v_i - d_i^T r_i^{(2)}.
\end{aligned} \tag{21}$$

Similarly, writing B_i as $\begin{pmatrix} B_i^{(1)} & B_i^{(2)} \end{pmatrix}$, where $B_i^{(1)}$ has k_i columns, we get

$$\begin{aligned}
x_{i+1} &= A_i x_i + B_i u_i + c_i \\
&= A_i x_i + B_i^{(1)} ((u_i)_j)_{j=1}^{k_i} + B_i^{(2)} ((u_i)_j)_{j=k_i+1}^{m_i} + c_i \\
&= A_i x_i + B_i^{(1)} v_i + B_i^{(2)} (-C_i x_i - F_i v_i - d_i) + c_i \\
&= (A_i - B_i^{(2)} C_i) x_i + (B_i^{(1)} - B_i^{(2)} F_i) v_i + (c_i - B_i^{(2)} d_i).
\end{aligned} \tag{22}$$

Finally, we can take

$$\begin{aligned}
R'_i &= R_i^{(1)} + G_i^T R_i^{(3)} G_i - 2R_i^{(2)} G_i \\
Q'_i &= Q_i + C_i^T R_i^{(3)} C_i - 2M_i^{(2)} C_i \\
M'_i &= M_i^{(1)} - M_i^{(2)} G_i - C_i^T R_i^{(2)} + C_i^T R_i^{(3)} G_i \\
A'_i &= A_i - B_i^{(2)} C_i \\
B'_i &= B_i^{(1)} - B_i^{(2)} F_i \\
q'_i &= C_i^T R_i^{(3)} d_i - M_i^{(2)} d_i - C_i^T R_i^{(2)} \\
r'_i &= d_i + G_i^T R_i^{(3)} d_i + r_i^{(1)} - G_i^T r_i^{(2)} \\
c'_i &= c_i - B_i^{(2)} d_i \\
E'_i &= E_i \\
e'_i &= e_i.
\end{aligned} \tag{23}$$

Note that

$$R'_i = \begin{pmatrix} I & -G_i^T \end{pmatrix} \begin{pmatrix} R_i^{(1)} & R_i^{(2)} \\ (R_i^{(2)})^T & R_i^{(3)} \end{pmatrix} \begin{pmatrix} I \\ -G_i \end{pmatrix}, \tag{24}$$

so clearly the R'_i matrices are positive definite, as the R_i matrices are positive definite.

Moreover,

$$\begin{pmatrix} Q'_i & M'_i \\ (M'_i)^T & R'_i \end{pmatrix} = \begin{pmatrix} I & 0 & -C_i^T \\ 0 & I & -G_i^T \end{pmatrix} \begin{pmatrix} Q_i & M_i^{(1)} & M_i^{(2)} \\ (M_i^{(1)})^T & R_i^{(1)} & R_i^{(2)} \\ (M_i^{(2)})^T & (R_i^{(2)})^T & R_i^{(3)} \end{pmatrix} \begin{pmatrix} I & 0 \\ 0 & I \\ -C_i & -G_i \end{pmatrix} \tag{25}$$

These are also positive semi-definite.

D. Eliminate stage $i + 1$ whenever $B_i = 0$

In the sequential version of our algorithm, this step can safely be skipped.

We will compute all maximal stage intervals $[i, j]$ for which $\forall k \in [i, j], B_k = 0$, and eliminate the corresponding stages $[i + 1, j + 1]$.

The first part can easily be parallelized: with $O(N^3)$ workers ($O(N)$ per (i, j) pair), we can independently check whether:

- $\forall k \in [i, j], B_k = 0$,
- $i = 0 \vee B_{i-1} \neq 0$,
- $j = N \vee B_{j+1} \neq 0$.

In order to eliminate a stage interval $[i + 1, j + 1]$, we need to compute all products $A_i, A_{i+1} A_i, \dots, A_{j+1} \dots A_i$. This can be done in $O(\log N \log n)$ using an associative scan [11], noting that the product of two $k \times k$ matrix has parallel runtime

complexity $O(\log k)$, as each of the k^2 dot products can be computed independently, again using an associative scan.

Any state-only equality constraints associated with stages $[i + 1, j + 1]$ get transformed into state-only equality constraints associated with stage i :

$$\begin{aligned}
E'_i &= \begin{pmatrix} E_i \\ E_{i+1} A_i \\ \dots \\ E_{j+1} A_j \dots A_i \end{pmatrix} \\
e'_i &= \begin{pmatrix} e_i \\ E_{i+1} c_i + e_{i+1} \\ \dots \\ E_{j+1} (\sum_{k=i}^j (\prod_{l=k+1}^j A_l^T)^T c_k) + e_{j+1} \end{pmatrix}
\end{aligned} \tag{26}$$

The post-stage-elimination dynamics become:

$$\begin{aligned}
x_{j+2} &= A_{j+1} x_{j+1} + B_{j+1} u_{j+1} + c_{j+1} \\
&= A_{j+1} A_j \dots A_i x_i + B_{j+1} u_{j+1} + \sum_{k=i}^{j+1} (\prod_{l=k+1}^{j+1} A_l^T)^T c_k.
\end{aligned} \tag{27}$$

We will also need to account for all cost terms involving x_{i+1}, \dots, x_{j+1} . Noting that the u_i, \dots, u_j don't participate in the dynamics, the following lemma will be useful.

Lemma 1. *Let $f(x, u) = \frac{1}{2} x^T Q x + x^T M u + \frac{1}{2} u^T R u + q^T x + r^T u$ and $g(x) = \min f(x, u)$. Then $g(x) = \frac{1}{2} x^T (Q - M R^{-1} M^T) x + (q - M R^{-1} r)^T x - \frac{1}{2} r^T R^{-1} r$, corresponding to $u = -R^{-1} (r + M^T x)$.*

Therefore,

$$\begin{aligned}
Q'_i &= \left(\prod_{k=i}^j A_k^T \right) Q_{j+1} \left(\prod_{k=i}^j A_k^T \right)^T \\
&\quad + \sum_{k=i}^j \left(\prod_{l=i}^{k-1} A_l^T \right) (Q_k - M_k R_k^{-1} M_k^T) \left(\prod_{l=i}^{k-1} A_l^T \right)^T \\
q'_i &= \left(\prod_{k=i}^j A_k^T \right) q_{j+1} \\
&\quad + \sum_{k=i}^j \left(\prod_{l=i}^{k-1} A_l^T \right) (q_k - M_k R_k^{-1} r_k + Q_k \sum_{p=i}^{k-1} \left(\prod_{l=p+1}^{k-1} A_l^T \right)^T c_p) \\
M'_i &= \left(\prod_{k=i}^j A_k^T \right) M_{j+1} \\
r'_i &= r_{j+1} + M_{j+1}^T \sum_{k=i}^j \left(\prod_{l=k+1}^j A_l^T \right)^T c_k.
\end{aligned} \tag{28}$$

E. Reduction to full row rank E_i

Similarly, whenever one of the E_i matrices does not have full row rank, we can pick a non-zero vector v such that $v^T E_i = 0$; if $v^T e_i \neq 0$, the problem is guaranteed to be infeasible, as $E_i x_i + e_i = 0$ admits no solutions; otherwise, we can remove any of the constraints in $E_i x_i + e_i = 0$

corresponding to an index with a non-zero value. This process can be repeated until E_i has full row rank or infeasibility has been established. This can be achieved in sequential runtime $O((s_i + t_i)n_i^3)$, as only the first $n_i + 1$ rows of E_i need to be considered at each iteration to find such a vector v . This can also be achieved in parallel runtime $O(\log^2 n_i)$, given that each set of $n_i + 1$ rows can be processed in parallel, and that $k \times k$ linear systems can be solved in $O(\log^2 k)$ parallel runtime, as shown in [10].

F. Reduction to $E_i = (F_i \ I)$ or $E_i = I$

If E_i is a square matrix, simply left-multiplying $E_i x_i + e_i = 0$ by E_i^{-1} achieves the intended reduction, and no more work is required.

Otherwise, since each E_i has full row rank, and given that row and column ranks must match (due to the fundamental theorem of linear algebra), we can find invertible matrices L_i and permutation matrices P_i such that $L_i E_i P_i^{-1} = (F_i \ I_{k_i})$, where k_i is number of rows of E_i .

Letting $y_i = P_i x_i$, we can reformulate our LQR problem in terms of the y_i instead.

$$\begin{aligned} x_{i+1} &= A_i x_i + B_i u_i + c_i \\ \Leftrightarrow P_{i+1} x_{i+1} &= (P_{i+1} A_i P_i^{-1})(P_i x_i) + (P_{i+1} B_i) u_i + P_{i+1} c_i \\ \Leftrightarrow y_{i+1} &= (P_{i+1} A_i P_i^{-1}) y_i + (P_{i+1} B_i) u_i + P_{i+1} c_i \end{aligned} \quad (29)$$

$$\begin{aligned} x_i^T Q_i x_i &= (P_i x_i)^T ((P_i^{-1})^T Q_i P_i^{-1}) (P_i x_i) \\ &= y_i^T ((P_i^{-1})^T Q_i P_i^{-1}) y_i \end{aligned} \quad (30)$$

$$q_i^T x_i = ((P_i^{-1})^T q_i)^T (P_i x_i) = ((P_i^{-1})^T q_i)^T y_i \quad (31)$$

$$\begin{aligned} x_i^T M_i u_i &= (P_i x_i)^T ((P_i^{-1})^T M_i) (u_i) \\ &= y_i^T ((P_i^{-1})^T M_i) u_i \end{aligned} \quad (32)$$

$$\begin{aligned} E_i x_i + e_i &= 0 \\ \Leftrightarrow (L_i E_i P_i^{-1})(P_i x_i) + L_i e_i &= 0 \\ \Leftrightarrow (L_i E_i P_i^{-1}) y_i + L_i e_i &= 0 \end{aligned} \quad (33)$$

Therefore, we can simply take

$$\begin{aligned} R'_i &= R_i \\ Q'_i &= (P_i^{-1})^T Q_i P_i^{-1} \\ M'_i &= (P_i^{-1})^T M_i \\ A'_i &= P_{i+1} A_i P_i^{-1} \\ B'_i &= P_{i+1} B_i \\ q'_i &= (P_i^{-1})^T q_i \\ r'_i &= r_i \\ c'_i &= P_{i+1} c_i \\ E'_i &= L_i E_i P_i^{-1} = (F_i \ I_{k_i}) \\ e'_i &= L_i e_i. \end{aligned} \quad (34)$$

G. Eliminating $E_i x_i + e_i = 0$

As above, there are two cases to consider.

If E_i is square, due to prior reductions, we know that $E_i = I$, and $E_i x_i + e_i = 0$ can be eliminated together with the state x_i , as $x_i = -e_i$ must hold. In this case, if $i = 0$, either $s_0 = -E_i^{-1} e_i$ (in which case we can simply eliminate this constraint) or the problem can be declared infeasible. If $i > 0$, we can alter the dynamics constraint determining x_i to become $x_i = 0x_{i-1} + 0u_{i-1} - E_i^{-1} e_i$. We must ensure, however, that the original dynamics are satisfied; as shown below, they get replaced by a new mixed state-and-control constraint on $i-1$:

$$\begin{aligned} x_i &= A_{i-1} x_{i-1} + B_{i-1} u_{i-1} + c_{i-1} \\ \Leftrightarrow -E_i^{-1} e_i &= A_{i-1} x_{i-1} + B_{i-1} u_{i-1} + c_{i-1} \\ \Leftrightarrow A_{i-1} x_{i-1} + B_{i-1} u_{i-1} + (C_{i-1} + E_i^{-1} e_i) &= 0 \end{aligned} \quad (35)$$

Note that this reduction required adding some new mixed state-and-control linear equality constraints back into the problem. This is not an issue, as the number of free state variables (i.e. those that are influenced by previous states or controls) was reduced, and the new mixed state-and-control linear equality constraints can be eliminated using the method of section II-B and section II-C.

If E_i is not a square matrix, due to prior reductions, we can write $E_i = (F_i \ I_{k_i})$, where k_i denotes the number of rows of E_i .

$$\begin{aligned} E_i x_i + e_i = 0 &\Leftrightarrow (F_i \ I) x_i + e_i = 0 \\ \Leftrightarrow ((x_i)_j)_{j=k_i+1}^{n_i} &= -F_i ((x_i)_j)_{j=1}^{k_i} - e_i \\ \Leftrightarrow x_i &= \begin{pmatrix} I_{k_i} \\ -F_i \end{pmatrix} ((x_i)_j)_{j=1}^{k_i} - \begin{pmatrix} 0 \\ e_i \end{pmatrix} \end{aligned} \quad (36)$$

We can use this to eliminate the variables $((x_i)_j)_{j=k_i+1}^{n_i}$ together with the constraints $E_i x_i + e_i = 0$, by plugging in this substitution rule in the constrained LQR problem definition.

For convenience, we let $y_i = ((x_i)_j)_{j=1}^{k_i}$. Moreover, we let

$$A_i = \begin{pmatrix} A_i^{(1)} & A_i^{(2)} \\ A_i^{(3)} & A_i^{(4)} \end{pmatrix}, B_i = \begin{pmatrix} B_i^{(1)} \\ B_i^{(2)} \end{pmatrix}, c_i = \begin{pmatrix} c_i^{(1)} \\ c_i^{(2)} \end{pmatrix}, \quad (37)$$

where $A_i^{(1)}$ has k_i columns and k_{i+1} rows, and both $B_i^{(1)}$ and $c_i^{(1)}$ have k_{i+1} rows.

$$\begin{aligned} x_{i+1} &= A_i x_i + B_i u_i + c_i \\ \Leftrightarrow \begin{pmatrix} I_{k_{i+1}} \\ -F_{i+1} \end{pmatrix} y_{i+1} - \begin{pmatrix} 0 \\ e_{i+1} \end{pmatrix} &= A_i \left(\begin{pmatrix} I_{k_i} \\ -F_i \end{pmatrix} y_i - \begin{pmatrix} 0 \\ e_i \end{pmatrix} \right) \\ &\quad + B_i u_i + c_i \\ \Leftrightarrow \begin{cases} y_{i+1} = (A_i^{(1)} - A_i^{(2)} F_i) y_i + B_i^{(1)} u_i + c_i^{(1)} \\ -F_{i+1} ((A_i^{(1)} - A_i^{(2)} F_i) y_i + B_i^{(1)} u_i + c_i^{(1)}) - e_{i+1} = \\ (A_i^{(3)} - A_i^{(4)} F_i) y_i - A_i^{(4)} e_i + B_i^{(2)} u_i + c_i^{(2)} \end{cases} \end{aligned} \quad (38)$$

Note that the old dynamics constraints over the x_i got replaced by new dynamics constraints over the lower-dimensional y_i , but new mixed state-and-control linear equality constraints got added back in. This is not a problem, as the number of state variables was reduced, and the new mixed

state-and-control linear equality constraints can be eliminated using the method of section II-B and section II-C.

$$\begin{aligned}
x_i^T Q_i x_i &= \left(\begin{pmatrix} I_{k_i} \\ -F_i \end{pmatrix} y_i - \begin{pmatrix} 0 \\ e_i \end{pmatrix} \right)^T Q_i \left(\begin{pmatrix} I_{k_i} \\ -F_i \end{pmatrix} y_i - \begin{pmatrix} 0 \\ e_i \end{pmatrix} \right) \\
&= y_i^T (I_{k_i} \quad -F_i^T) Q_i \begin{pmatrix} I_{k_i} \\ -F_i \end{pmatrix} y \\
&\quad - 2 \left(\begin{pmatrix} I_{k_i} \quad -F_i^T \end{pmatrix} Q_i \begin{pmatrix} 0 \\ e_i \end{pmatrix} \right)^T y_i \\
&\quad + \begin{pmatrix} 0 & e_i^T \end{pmatrix} Q_i \begin{pmatrix} 0 \\ e_i \end{pmatrix}
\end{aligned} \tag{39}$$

$$\begin{aligned}
q_i^T x_i &= q_i^T \left(\begin{pmatrix} I_{k_i} \\ -F_i \end{pmatrix} y_i - \begin{pmatrix} 0 \\ e_i \end{pmatrix} \right) \\
&= \left(\begin{pmatrix} I_{k_i} \quad -F_i^T \end{pmatrix} q_i \right)^T y_i - q_i^T \begin{pmatrix} 0 \\ e_i \end{pmatrix}
\end{aligned} \tag{40}$$

$$\begin{aligned}
x_i^T M_i u_i &= \left(\begin{pmatrix} I_{k_i} \\ -F_i \end{pmatrix} y_i - \begin{pmatrix} 0 \\ e_i \end{pmatrix} \right)^T M_i u_i \\
&= y_i^T (I_{k_i} \quad -F_i^T) M_i u_i - (M_i^T \begin{pmatrix} 0 & e_i^T \end{pmatrix})^T u_i
\end{aligned} \tag{41}$$

Therefore, we can take

$$\begin{aligned}
R'_i &= R_i \\
Q'_i &= (I_{k_i} \quad -F_i^T) Q_i \begin{pmatrix} I_{k_i} \\ -F_i \end{pmatrix} \\
M'_i &= (I_{k_i} \quad -F_i^T) M_i \\
A'_i &= A_i^{(1)} - A_i^{(2)} F_i \\
B'_i &= B_i^{(1)} \\
q'_i &= (I_{k_i} \quad -F_i^T) (q_i - 2Q_i \begin{pmatrix} 0 \\ e_i \end{pmatrix}) \\
r'_i &= r_i - M_i^T \begin{pmatrix} 0 & e_i^T \end{pmatrix} \\
c'_i &= c_i^{(1)} \\
C'_i &= A_i^{(3)} - A_i^{(4)} F_i + F_{i+1} (A_i^{(1)} - A_i^{(2)} F_i) \\
D'_i &= B_i^{(2)} + F_{i+1} B_i^{(1)} \\
d'_i &= c_i^{(2)} - A_i^{(4)} e_i + F_{i+1} c_i^{(1)} + e_{i+1}.
\end{aligned} \tag{42}$$

Note that

$$\begin{pmatrix} Q'_i & M'_i \\ (M'_i)^T & R'_i \end{pmatrix} = \begin{pmatrix} (I_{k_i} \quad -F_i^T) & 0 \\ 0 & I \end{pmatrix} \begin{pmatrix} Q_i & M_i \\ M_i^T & R_i \end{pmatrix} \begin{pmatrix} \begin{pmatrix} I_{k_i} \\ -F_i \end{pmatrix} & 0 \\ 0 & I \end{pmatrix} \tag{43}$$

Therefore, the required positive (semi-)definiteness properties are preserved.

H. Solving the LQR problem

After the reductions described above have been completed, we are left with an unconstrained LQR problem.

An algorithm for efficiently solving such problems in $O(\log m + \log n \log N)$ parallel runtime is already known; see [3] and [9].

I. Retrieve the eliminated state and control variables

In the reductions presented above, whenever variables were eliminated, rules for recovering the eliminated variables were presented. Similarly, whenever a change of variables occurred, the original variables can be recovered by a simple permutation of the new ones. The cumulative transformations from the latest variables to the original ones can always be expressed as stagewise affine functions, and are therefore easy to compose.

J. Computational Complexity

The sequential runtime of the full method is straightforward. Based on prior discussions, we can upper bound it by $O((s + t + N) \max(m, n)^3)$.

The parallel runtime is also easy to characterize, once we bound the number of iterations required for eliminating all linear equality constraints.

Theorem 2. *After $n + 1$ iterations of our parallel algorithm, all linear equality constraints will have been eliminated.*

Proof. To establish this result, we will analyze what may happen to the state-only equality constraints associated with a single stage, and show that they get fully eliminated after $2(n + 1)$ iterations.

The elimination of the state-only constraints at a certain stage may result in n new mixed state-and-control constraints being added to the previous stage. Given that we ensure that the matrix B_i at that previous stage is nonzero, at least one of the n new mixed state-and-control constraints will be eliminated in the next iteration, and at most $n - 1$ mixed state-and-control constraints will be propagated back in the next iteration. After $n + 1$ steps, no more constraints get propagated back. \square

Therefore, combining this with prior discussions around the complexity of each step, the parallel runtime of the entire method is upper bounded by $O(\log n \log N + n \log^2 \max(m, n))$.

III. CONCLUSION

We introduced the first efficient parallel algorithm for solving constrained LQR problems.

This was achieved by deriving techniques for eliminating the linear equality constraints present in the original problem, while preserving the standard positive (semi-)definiteness requirements. These techniques relied exclusively on simple linear-algebra decompositions.

Once the constraints are eliminated, we resort to well-established parallel algorithms for solving the resulting unconstrained LQR problem, and recover the original variables by book-keeping and inverting the sequence of variable eliminations or changes.

The method we introduced unlocks substantial speedups in solving nonlinear constrained discrete-time optimal control problems, as typical solution mechanisms rely on solving constrained LQR problems as a key subroutine.

REFERENCES

- [1] David Mayne. 1966. “A Second-Order Gradient Method for Determining Optimal Trajectories of Non-Linear Discrete-Time Systems.” *International Journal of Control* 3 (1): 85–95. <https://doi.org/10.1080/00207176608921369>.
- [2] Joseph C. Dunn and Dimitri P. Bertsekas. 1989. “Efficient Dynamic Programming Implementations of Newton’s Method for Unconstrained Optimal Control Problems.” *Journal of Optimization Theory and Applications* 63: 23–38. <https://doi.org/10.1007/BF00940728>.
- [3] João Sousa-Pinto, and Dominique Orban. 2024. “Primal-Dual iLQR.” *arXiv* <https://arxiv.org/pdf/2403.00748>.
- [4] Christopher V. Rao, Stephen J. Wright, and James B. Rawlings. 1998. “Application of Interior-Point Methods to Model Predictive Control.” *Journal of Optimization Theory and Applications* 99 (3): 723–57.
- [5] Lander Vanroye, Ajay Sathya, Joris De Schutter, and Wilm Decré. 2023. “FATROP: A Fast Constrained Optimal Control Problem Solver for Robot Trajectory Optimization and Control.” *arXiv*. <https://doi.org/10.48550/arXiv.2303.16746>.
- [6] Forrest Laine, and Claire Tomlin. 2019. “Efficient Computation of Feedback Control for Equality-Constrained LQR.” *International Conference on Robotics and Automation (ICRA)* 6748–6754. <http://doi.org/10.1109/ICRA.2019.8793566>.
- [7] Athanasios Sideris and Luis A. Rodriguez. 2011. “A Riccati approach for constrained linear quadratic optimal control” *International Journal of Control* 84 (2): 370–380 <http://dx.doi.org/10.1080/00207179.2011.555883>
- [8] Lander Vanroye, Joris De Schutter, and Wilm Decré. 2023. “A generalization of the riccati recursion for equality-constrained linear quadratic optimal control.” *arXiv* <https://arxiv.org/abs/2302.14836>.
- [9] Simo Särkkä and Ángel F. García-Fernández. 2023. “Temporal Parallelization of Dynamic Programming and Linear Quadratic Control.” *IEEE Transactions on Automatic Control* 68 (2): 851–866, <https://doi.org/10.1109/TAC.2022.3147017>.
- [10] Lazlo Csanky. 1976. “Fast Parallel Matrix Inversion Algorithms.” *SIAM Journal on Computing* 5 (4): 618–623, <https://doi.org/10.1137/0205040>.
- [11] Guy E. Blelloch. 1989. “Scans as primitive parallel operations” *IEEE Transactions on Computers* 38 (11): 1526–1538 <https://doi.org/10.1109/12.42122>