

Load Balancing Harmonic VOS

Version 1.0.0



Table of Contents

1. About this Brief	3
2. Loadbalancer.org Appliances Supported	3
3. Software Versions Supported	3
3.1. Loadbalancer.org Appliance	3
3.2. Harmonic VOS	3
4. Harmonic VOS	3
5. Load Balancing Harmonic VOS	3
5.1. Load Balancing & HA Requirements	4
5.2. Virtual Service (VIP) Requirements	4
6. Deployment Concept	4
7. Load Balancer Deployment Methods	5
7.1. Layer 4 DR Mode	5
7.2. Layer 7 SNAT Mode	6
8. Configuring Harmonic VOS for Load Balancing	7
8.1. Layer 7 SNAT Mode VIPs	7
8.2. Layer 4 DR Mode VIPs	7
8.2.1. Windows Server 2012 & Later	7
9. Loadbalancer.org Appliance – the Basics	12
9.1. Virtual Appliance	12
9.2. Initial Network Configuration	13
9.3. Accessing the Appliance WebUI	13
9.3.1. Main Menu Options	14
9.4. Appliance Software Update	15
9.4.1. Online Update	15
9.4.2. Offline Update	15
9.5. Ports Used by the Appliance	16
9.6. HA Clustered Pair Configuration	17
10. Appliance Configuration for Harmonic VOS	17
10.1. VIP 1 - Harmonic_Management	17
10.1.1. Virtual Service (VIP) Configuration	17
10.1.2. Configure the Associated Real Servers (RIPs)	18
10.2. VIP 2 - Harmonic_Traffic	18
10.2.1. Virtual Service (VIP) Configuration	18
10.2.2. Configure the Associated Real Servers (RIPs)	19
10.3. Finalizing the Configuration	20
11. Testing & Verification	20
11.1. Accessing Harmonic VOS via the Load Balancer	20
11.2. Using System Overview	20
12. Technical Support	21
13. Further Documentation	21
14. Appendix	22
14.1. Configuring HA - Adding a Secondary Appliance	22
14.1.1. Non-Replicated Settings	22
14.1.2. Configuring the HA Clustered Pair	23
15. Document Revision History	25

1. About this Brief

This brief outlines the steps required to configure a load balanced Harmonic VOS environment utilizing Loadbalancer.org appliances. It covers the configuration of the load balancers and also any Harmonic VOS configuration changes that are required to enable load balancing.

For more information about initial appliance deployment, network configuration and using the Web User Interface (WebUI), please also refer to the [Administration Manual](#).

2. Loadbalancer.org Appliances Supported

All our products can be used with Harmonic VOS. For full specifications of available models please refer to <https://www.loadbalancer.org/products/enterprise>.

Some features may not be available or fully supported in all cloud platforms due to platform specific limitations. For more details, please refer to the "Main Differences to our Standard (Non-Cloud) Product" section in the appropriate cloud platform Quick Start Guide or check with Loadbalancer.org support.

3. Software Versions Supported

3.1. Loadbalancer.org Appliance

- V8.9.1 and later

 **Note**

The screenshots used throughout this document aim to track the latest Loadbalancer.org software version. If you're using an older version, or the very latest, the screenshots presented here may not match your WebUI exactly.

3.2. Harmonic VOS

- All versions

4. Harmonic VOS

Harmonic VOS Media Software is a comprehensive, software-based platform that streamlines the entire video workflow—from playout and encoding to packaging and origin delivery. Designed to support both broadcast and OTT applications, it provides a unified, highly scalable foundation for modern media operations. As a cloud-native, container-based solution, it enables flexible, efficient deployment across private data centers as well as private or public cloud environments, ensuring optimal performance and adaptability.

5. Load Balancing Harmonic VOS

 **Note**

It's highly recommended that you have a working Harmonic VOS environment first before implementing the load balancer.



5.1. Load Balancing & HA Requirements

Harmonic VOS can be installed on multiple servers and load balanced to provide load sharing, HA and resilience. The following protocols can be load balanced:

- **HTTP/HTTPS traffic** – For REST API requests or web-based interactions with the VOS system. This traffic is essential for control, configuration, and monitoring of the VOS services.
- **RTSP (Real-Time Streaming Protocol)** – For streaming video feeds between encoders/decoders, players, or servers, especially for live video streaming.
- **RTMP (Real-Time Messaging Protocol)** – Often used for streaming video to platforms or for broadcasting live media.
- **UDP/TCP traffic** – Used for media streams, especially in transport protocols like MPEG-TS (Transport Stream) or other packetized video formats.


5.2. Virtual Service (VIP) Requirements

To provide load balancing and HA for Harmonic VOS, the following VIPs are required:

Ref.	VIP Name	Mode	Port(s)	Persistence Mode	Health Check
VIP 1	Harmonic_Management	L7 SNAT	8080,8443	Source IP	HTTPS (GET)
VIP 2	Harmonic_Traffic	L4 DR	1935,554,50000-65535	Source IP	HTTPS (GET)

6. Deployment Concept

Once the load balancer is deployed, clients connect to the Virtual Services (VIPs) rather than connecting directly to one of the Harmonic VOS servers. These connections are then load balanced across the Harmonic VOS servers to distribute the load according to the load balancing algorithm selected.



Note

The load balancer can be deployed as a single unit, although Loadbalancer.org recommends a clustered pair for resilience & high availability. Please refer to the section [Configuring HA - Adding a Secondary Appliance](#) in the appendix for more details on configuring a clustered pair.

7. Load Balancer Deployment Methods

The load balancer can be deployed in 4 fundamental ways: *Layer 4 DR mode*, *Layer 4 NAT mode*, *Layer 4 SNAT mode*, and *Layer 7 SNAT mode*.


For Harmonic VOS, Layer 4 DR mode and layer 7 SNAT mode are recommended. These modes are described below and are used for the configuration presented in this guide.

7.1. Layer 4 DR Mode

Layer 4 DR (Direct Routing) mode is a very high performance solution that requires little change to your existing infrastructure. The image below shows an example network diagram for this mode.

Note

Kemp, Brocade, Barracuda & A10 Networks call this *Direct Server Return* and F5 call it *nPath*.




- DR mode works by changing the destination MAC address of the incoming packet to match the selected Real Server on the fly which is very fast.
- When the packet reaches the Real Server it expects the Real Server to own the Virtual Services IP address (VIP). This means that each Real Server (and the load balanced application) must respond to both the Real Server's own IP address and the VIP.
- The Real Server should not respond to ARP requests for the VIP. Only the load balancer should do this. Configuring the Real Server in this way is referred to as "Solving the ARP Problem". For more information please refer to [DR Mode Considerations](#).

- On average, DR mode is 8 times quicker than NAT mode for HTTP and much faster for other applications such as Remote Desktop Services, streaming media and FTP.
- The load balancer must have an interface in the same subnet as the Real Servers to ensure layer 2 connectivity which is required for DR mode to operate.
- The VIP can be brought up on the same subnet as the Real Servers or on a different subnet provided that the load balancer has an interface in that subnet.
- Port translation is not possible with DR mode, e.g. VIP:80 → RIP:8080 is not supported.
- DR mode is transparent, i.e. the Real Server will see the source IP address of the client.

7.2. Layer 7 SNAT Mode

Layer 7 SNAT mode uses a proxy (HAProxy) at the application layer. Inbound requests are terminated on the load balancer and HAProxy generates a new corresponding request to the chosen Real Server. As a result, Layer 7 is typically not as fast as the Layer 4 methods. Layer 7 is typically chosen when either enhanced options such as SSL termination, cookie based persistence, URL rewriting, header insertion/deletion etc. are required, or when the network topology prohibits the use of the layer 4 methods. The image below shows an example network diagram for this mode.



- Because layer 7 SNAT mode is a full proxy, Real Servers in the cluster can be on any accessible network including across the Internet or WAN.
- Layer 7 SNAT mode is not transparent by default, i.e. the Real Servers will not see the source IP address of the client, they will see the load balancer's own IP address by default, or any other local appliance IP address if preferred (e.g. the VIP address). This can be configured per layer 7 VIP. If required, the load balancer can be configured to provide the actual client IP address to the Real Servers in 2 ways. Either by inserting a header that contains the client's source IP address, or by modifying the Source Address field of the IP packets and replacing the IP address of the load balancer with the IP address of the client. For more information on these methods please refer to [Transparency at Layer 7](#).

- Layer 7 SNAT mode can be deployed using either a one-arm or two-arm configuration. For two-arm deployments, **eth1** is typically used for client side connections and **eth0** is used for Real Server connections, although this is not mandatory since any interface can be used for any purpose.
- Requires no mode-specific configuration changes to the load balanced Real Servers.
- Port translation is possible with Layer 7 SNAT mode, e.g. VIP:80 → RIP:8080 is supported.
- You should not use the same RIP:PORT combination for layer 7 SNAT mode VIPs and layer 4 SNAT mode VIPs because the required firewall rules conflict.

8. Configuring Harmonic VOS for Load Balancing

8.1. Layer 7 SNAT Mode VIPs

Layer 7 SNAT mode VIPs do not require any mode specific configuration changes to the load balanced Real Servers.

8.2. Layer 4 DR Mode VIPs

Layer 4 DR mode VIPs require the "ARP problem" to be solved on each load balanced Real Server. This enables DR mode to work correctly.

Detailed steps on solving the "ARP problem" for Windows 2012 & later are presented below. These steps must be followed on each Real Server.

8.2.1. Windows Server 2012 & Later

Windows Server 2012 and later support Direct Routing (DR) mode through the use of the Microsoft Loopback Adapter that must be installed and configured on each load balanced (Real) Server. The IP address configured on the Loopback Adapter must be the same as the Virtual Service (VIP) address. This enables the server to receive packets that have their destination set as the VIP address. If a Real Server is included in multiple DR mode VIPs, an IP address for each VIP must be added to the Loopback Adapter.


In addition, the strong/weak host behavior must be configured on each Real Server. The weak host model allows packets with any IP to be sent or received via an interface. The strong host model only allows packets with an IP belonging to the interface to be sent or received.

(!) Important The following 3 steps must be completed on **all** Real Servers associated with the VIP.

Step 1 of 3: Install the Microsoft Loopback Adapter

1. Click **Start**, then run **hdwwiz** to start the Hardware Installation Wizard.
2. Once the Wizard has started, click **Next**.
3. Select **Install the hardware that I manually select from a list (Advanced)**, click **Next**.
4. Select **Network adapters**, click **Next**.





5. Select **Microsoft & Microsoft KM-Test Loopback Adapter**, click **Next**.

6. Click **Next** to start the installation, when complete click **Finish**.

Step 2 of 3: Configure the Loopback Adapter

1. Open Control Panel and click **Network and Sharing Center**.

2. Click **Change adapter settings**.

3. Right-click the new Loopback Adapter and select **Properties**.


Note

You can configure IPv4 or IPv6 addresses or both depending on your requirements.


IPv4 Addresses

1. Uncheck all items except **Internet Protocol Version 4 (TCP/IPv4)** as shown below:





2. Ensure that **Internet Protocol Version (TCP/IPv4)** is selected, click **Properties** and configure the IP address to be the same as the Virtual Service address (VIP) with a subnet mask of **255.255.255.255**, e.g. **192.168.2.20/255.255.255.255** as shown below:



Note **192.168.2.20** is an example, make sure you specify the correct VIP address.


Note If a Real Server is included in multiple DR mode VIPs, an IP address for each VIP must be added to the Loopback Adapter.



3. Click **OK** then click **Close** to save and apply the new settings.


IPv6 Addresses

1. Uncheck all items except **Internet Protocol Version 6 (TCP/IPv6)** as shown below:



2. Ensure that **Internet Protocol Version (TCP/IPv6)** is selected, click **Properties** and configure the IP address to be the same as the Virtual Service (VIP) and set the **Subnet Prefix Length** to be the same as your network setting, e.g. **2001:470:1f09:e72::15/64** as shown below:





Note 2001:470:1f09:e72::15/64 is an example, make sure you specify the correct VIP address.

Note If a Real Server is included in multiple DR mode VIPs, an IP address for each VIP must be added to the Loopback Adapter.

3. Click **OK** then click **Close** to save and apply the new settings.

Step 3 of 3: Configure the strong/weak host behavior

The strong/weak host behavior can be configured using either of the following 2 methods:

- Option 1 - Using network shell (netsh) commands
- Option 2 - Using PowerShell cmdlets

The commands in this section assume that the LAN Adapter is named "net" and the Loopback Adapter is named "loopback" as shown in the example below:



① Important

Either adjust the commands to use the names allocated to your LAN and loopback adapters, or rename the adapters before running the commands. Names are case sensitive so make sure



that the interface names used in the commands match the adapter names exactly.

Option 1 - Using Network Shell (netsh) Commands

To configure the correct strong/weak host behavior run the following commands:

For IPv4 addresses:

```
netsh interface ipv4 set interface "net" weakhostreceive=enabled  
netsh interface ipv4 set interface "loopback" weakhostreceive=enabled  
netsh interface ipv4 set interface "loopback" weakhostsend=enabled
```

For IPv6 addresses:

```
netsh interface ipv6 set interface "net" weakhostreceive=enabled  
netsh interface ipv6 set interface "loopback" weakhostreceive=enabled  
netsh interface ipv6 set interface "loopback" weakhostsend=enabled  
netsh interface ipv6 set interface "loopback" dadtransmits=0
```

Option 2 - Using PowerShell Cmdlets

For IPv4 addresses:

```
Set-NetIpInterface -InterfaceAlias loopback -WeakHostReceive enabled -WeakHostSend enabled  
-AddressFamily IPv4
```

```
Set-NetIpInterface -InterfaceAlias net -WeakHostReceive enabled -AddressFamily IPv4
```

For IPv6 Addresses:

```
Set-NetIpInterface -InterfaceAlias loopback -WeakHostReceive enabled -WeakHostSend enabled  
-DadTransmits 0 -AddressFamily IPv6
```

```
Set-NetIpInterface -InterfaceAlias net -WeakHostReceive enabled -AddressFamily IPv6
```

9. Loadbalancer.org Appliance – the Basics

9.1. Virtual Appliance

A fully featured, fully supported 30 day trial is available if you are conducting a PoC (Proof of Concept) deployment. The VA is currently available for VMware, Virtual Box, Hyper-V, KVM, XEN and Nutanix AHV and has been optimized for each Hypervisor. By default, the VA is allocated 2 vCPUs, 4GB of RAM and has a 20GB virtual disk. The Virtual Appliance can be downloaded [here](#).



i Note

The same download is used for the licensed product, the only difference is that a license key file (supplied by our sales team when the product is purchased) must be applied using the appliance's WebUI.

i Note

Please refer to [Virtual Appliance Installation](#) and the [ReadMe.txt](#) text file included in the VA download for additional information on deploying the VA using the various Hypervisors.

i Note

The VA has 4 network adapters. For VMware only the first adapter (**eth0**) is connected by default. For HyperV, KVM, XEN and Nutanix AHV all adapters are disconnected by default. Use the network configuration screen within the Hypervisor to connect the required adapters.

9.2. Initial Network Configuration

After boot up, follow the instructions on the appliance console to configure the management IP address, subnet mask, default gateway, DNS servers and other network and administrative settings.

(!) Important

Be sure to set a secure password for the load balancer, when prompted during the setup routine.

9.3. Accessing the Appliance WebUI

The WebUI is accessed using a web browser. By default, users are authenticated using Apache authentication. Users can also be authenticated against LDAP, LDAPS, Active Directory or Radius - for more information, please refer to [External Authentication](#).

i Note

There are certain differences when accessing the WebUI for the cloud appliances. For details, please refer to the relevant [Quick Start / Configuration Guide](#).

1. Using a browser, navigate to the following URL:

<https://<IP-address-configured-during-the-network-setup-wizard>:9443/lbadmin/>

i Note

You'll receive a warning about the WebUI's SSL certificate. This is due to the default self signed certificate that is used. If preferred, you can upload your own certificate - for more information, please refer to [Appliance Security Features](#).

i Note

If you need to change the port, IP address or protocol that the WebUI listens on, please refer to [Service Socket Addresses](#).

2. Log in to the WebUI using the following credentials:

Username: loadbalancer

Password: <configured-during-network-setup-wizard>





To change the password, use the WebUI menu option: *Maintenance > Passwords*.

Once logged in, the WebUI will be displayed as shown below:

LOADBALANCER

Enterprise **VA Max**

System Overview

WARNING: YOUR TRIAL IS DUE TO EXPIRE IN 30 DAYS.

Buy with confidence. All purchases come with a 90 day money back guarantee.
Already bought? Enter your license key [here](#)

Buy Now

System Overview [?](#)

2025-05-08 12:37:21 UTC

Would you like to run the Setup Wizard?

Accept **Dismiss**

Network Bandwidth

Bytes/s

200 k, 150 k, 100 k, 50 k, 0

Wed 18:00, Thu 00:00, Thu 06:00, Thu 12:00

RX 28 Min, 2713 Avg, 27344772 Total,
TX 0 Min, 13777 Avg, 138872181 Total,

System Load Average

System Load

1.0, 0.8, 0.6, 0.4, 0.2, 0.0

Wed 18:00, Thu 00:00, Thu 06:00, Thu 12:00

1m average 0.00 Min, 0.08 Avg, 0.68 Max
5m average 0.00 Min, 0.04 Avg, 0.30 Max
15m average 0.00 Min, 0.02 Avg, 0.12 Max

Memory Usage

3. You'll be asked if you want to run the Setup Wizard. Click **Dismiss** if you're following a guide or want to configure the appliance manually. Click **Accept** to start the Setup Wizard.



The Setup Wizard can only be used to configure Layer 7 services.

9.3.1. Main Menu Options

System Overview - Displays a graphical summary of all VIPs, RIPv2 and key appliance statistics

Local Configuration - Configure local host settings such as IP address, DNS, system time etc.

Cluster Configuration - Configure load balanced services such as VIPs & RIPv2



Maintenance - Perform maintenance tasks such as service restarts and creating backups

View Configuration - Display the saved appliance configuration settings

Reports - View various appliance reports & graphs

Logs - View various appliance logs

Support - Create a support download, contact the support team & access useful links

Live Chat - Start a live chat session with one of our Support Engineers

9.4. Appliance Software Update

We recommend that the appliance is kept up to date to ensure that you benefit from the latest bug fixes, security updates and feature improvements. Both online and offline update are supported.

Note

For full details, please refer to [Appliance Software Update](#) in the Administration Manual.

Note

Services may need to be restarted/reloaded after the update process completes or in some cases a full appliance restart may be required. We therefore recommend performing the update during a maintenance window.

9.4.1. Online Update

The appliance periodically contacts the Loadbalancer.org update server (**update.loadbalancer.org**) and checks for updates. This is the default behavior and can be disabled if preferred. If an update is found, a notification similar to the example below will be displayed at the top of the WebUI:

Information: Update 8.13.2 is now available for this appliance.

Online Update

Click **Online Update**. A summary of all new features, improvements, bug fixes and security updates included in the update will be displayed. Click **Update** at the bottom of the page to start the update process.

(?) Important

Do not navigate away whilst the update is ongoing, this may cause the update to fail.

The update can take several minutes depending on download speed and upgrade version. Once complete, the following message will be displayed:

Information: Update completed successfully. Return to system overview.

If services need to be reloaded/restarted or the appliance needs a full restart, you'll be prompted accordingly.

9.4.2. Offline Update

If the appliance does not have access to the Internet, offline update can be used.



To check for the latest version, please refer to our product roadmap page available [here](#). To obtain the latest offline update files contact support@loadbalancer.org.

To perform an offline update:

1. Using the WebUI, navigate to: **Maintenance > Software Update**.
2. Select **Offline Update**.
3. The following screen will be displayed:

Software Update

Offline Update

The following steps will lead you through offline update.

1. Contact **Loadbalancer.org support** to obtain the offline update archive and checksum.
2. Save the archive and checksum to your local machine.
3. Select the archive and checksum files in the upload form below.
4. Click *Upload and Install* to begin the update process.

Archive: No file chosen

Checksum: No file chosen

4. Select the **Archive** and **Checksum** files.
5. Click **Upload and Install**.
6. If services need to be reloaded/restarted or the appliance needs a full restart, you'll be prompted accordingly.

9.5. Ports Used by the Appliance

By default, the appliance uses the following TCP & UDP ports:

Protocol	Port	Purpose
TCP	22 *	SSH
TCP & UDP	53 *	DNS / GSLB
TCP & UDP	123	NTP
TCP & UDP	161 *	SNMP
UDP	6694	Heartbeat between Primary & Secondary appliances in HA mode
TCP	7778	HAProxy persistence table replication
TCP	9000 *	Gateway service (Centralized/Portal Management)
TCP	9080 *	WebUI - HTTP (disabled by default)
TCP	9081 *	Nginx fallback page
TCP	9443 *	WebUI - HTTPS



Protocol	Port	Purpose
TCP	25565 *	Shuttle service (Centralized/Portal Management)

Note

The ports used for SSH, GSLB, SNMP, the WebUI, the fallback page, the gateway service and the shuttle service can be changed if required. For more information, please refer to [Service Socket Addresses](#).

9.6. HA Clustered Pair Configuration

Loadbalancer.org recommend that load balancer appliances are deployed in pairs for high availability. In this guide a single unit is deployed first, adding a secondary unit is covered in the section [Configuring HA - Adding a Secondary Appliance](#) of the appendix.

10. Appliance Configuration for Harmonic VOS

10.1. VIP 1 - Harmonic_Management

10.1.1. Virtual Service (VIP) Configuration

1. Using the WebUI, navigate to *Cluster Configuration > Layer 7 – Virtual Services* and click **Add a new Virtual Service**.

Virtual Service		[Advanced +]
Label	Harmonic_Management	?
IP Address	192.168.94.100	?
Ports	8080,8443	?

Protocol		[Advanced +]
Layer 7 Protocol	TCP Mode	?

Cancel Update

2. Enter a suitable *Label* (name) for the Virtual Service, e.g. **Harmonic_Management**.
3. Set the *Virtual Service IP Address* field to the required IP address, e.g. **192.168.94.100**.
4. Set *Ports* to **8080,8443**.
5. Set the *Layer 7 Protocol* to **TCP Mode**.
6. Click **Update**.
7. Now click **Modify** next to the newly created VIP.
8. Scroll down to the *Health Checks* section.
 - Set *Health Checks* to **Negotiate HTTPS (GET)**.



- Set *Request to Send* to **/admin/status**.
- Set *Response Expected* to **Equals** and set the value to **Healthy**.

9. Click **Update**.

10.1.2. Configure the Associated Real Servers (RIPs)

1. Using the WebUI, navigate to *Cluster Configuration > Layer 7 – Real Servers* and click on **Add a new Real Server** next to the newly created VIP.

Label	HM1	?
Real Server IP Address	192.168.94.105	?
Real Server Port		?
Re-Encrypt to Backend	<input type="checkbox"/>	?
Weight	100	?
		Cancel Update

2. Enter a suitable *Label* (name) for the Real Server, e.g. **HM1**.
3. Set the *Real Server IP Address* field to the required IP address, e.g. **192.168.94.105**.
4. Leave the *Real Server Port* field blank.
5. Click **Update**.
6. Repeat these steps to add additional Real Servers as required.

10.2. VIP 2 - Harmonic_Traffic

10.2.1. Virtual Service (VIP) Configuration

1. Using the WebUI, navigate to *Cluster Configuration > Layer 4 – Virtual Services* and click **Add a new Virtual Service**.



Virtual Service

Label	Harmonic_Traffic	?
IP Address	192.168.94.110	?
Ports	1935,554,50000-65535	?

Protocol

Protocol	TCP/UDP	?
----------	---------	---

Forwarding

Forwarding Method	Direct Routing	?
-------------------	----------------	---

Cancel
Update

2. Enter a suitable *Label* (name) for the Virtual Service, e.g. **Harmonic_Traffic**.
3. Set the *Virtual Service IP Address* field to the required IP address, e.g. **192.168.94.110**.
4. Set *Ports* to **1935,554,50000-65535**.
5. Set the *Protocol* to **TCP/UDP**.
6. Leave *Forwarding Method* set to **Direct Routing**.
7. Click **Update**.
8. Now click **Modify** next to the newly created VIP.
9. Scroll down to the *Health Checks* section.
 - Set *Check Type* to **Negotiate**.
 - Set *Protocol* to **HTTPS**.
 - Set *Request to Send* to **/admin/status**.
 - Set *Response Expected* to **Healthy**.
10. Click **Update**.

10.2.2. Configure the Associated Real Servers (RIPs)

1. Using the WebUI, navigate to *Cluster Configuration > Layer 4 – Real Servers* and click on **Add a new Real Server** next to the newly created VIP.

Label	HT1	?
Real Server IP Address	192.168.94.115	?
Weight	100	?
Minimum Connections	0	?
Maximum Connections	0	?

Cancel
Update

Enter a suitable *Label* (name) for the Real Server, e.g. **HT1**.

2. Set the *Real Server IP Address* field to the required IP address, e.g. **192.168.94.115**.
3. Click **Update**.
4. Repeat these steps to add additional Real Servers as required.

10.3. Finalizing the Configuration

To apply the new settings, HAProxy must be reloaded. This can be done using the button in the "Commit changes" box at the top of the screen or by using the Restart Services menu option:

1. Using the WebUI, navigate to: **Maintenance > Restart Services**.
2. Click **Reload HAProxy**.

11. Testing & Verification

Note

For additional guidance on diagnosing and resolving any issues you may have, please also refer to [Diagnostics & Troubleshooting](#).

11.1. Accessing Harmonic VOS via the Load Balancer

Verify that you're able to successfully access all load balanced applications and services via the Virtual Services on the load balancer.

Note

Make sure that DNS is updated so that any FQDNs used point to the VIPs rather than individual servers.

11.2. Using System Overview

The System Overview can be viewed in the WebUI. It shows a graphical view of all Virtual Services & the associated Real Servers (i.e. the Harmonic VOS servers) and shows the state/health of each server as well as the overall state of each cluster. The example below shows that all servers are healthy (green) and available to accept connections:



VIRTUAL SERVICE	IP	PORTS	CONNNS	PROTOCOL	METHOD	MODE	
REAL SERVER	IP	PORTS	WEIGHT	CONNNS			
 Harmonic_Management	192.168.94.100	8080,8443	0	TCP	Layer 7	Proxy	
REAL SERVER	IP	PORTS	WEIGHT	CONNNS			
 HM1	192.168.94.105	8080,8443	100	0	Drain	Halt	
 HM2	192.168.94.106	8080,8443	100	0	Drain	Halt	
 Harmonic_Traffic	192.168.94.110	554,1935,..	0	TCPUDP	Layer 4	DR	
REAL SERVER	IP	PORTS	WEIGHT	CONNNS			
 HT1	192.168.94.115	554,1935,5..	100	0	Drain	Halt	
 HT2	192.168.94.116	554,1935,5..	100	0	Drain	Halt	

12. Technical Support

For more details about configuring the appliance and assistance with designing your deployment please don't hesitate to contact the support team using the following email address: support@loadbalancer.org.

13. Further Documentation

For additional information, please refer to the [Administration Manual](#).

14. Appendix

14.1. Configuring HA - Adding a Secondary Appliance

Our recommended configuration is to use a clustered HA pair of load balancers to provide a highly available and resilient load balancing solution. We recommend that the Primary appliance is fully configured first, then the Secondary appliance can be added to create an HA pair. Once the HA pair is configured, load balanced services must be configured and modified on the Primary appliance. The Secondary appliance will be automatically kept in sync.

 **Note**

For Enterprise Azure, the HA pair should be configured first. For more information, please refer to the Azure Quick Start/Configuration Guide available in the [documentation library](#)

The clustered HA pair uses Heartbeat to determine the state of the other appliance. Should the active device (normally the Primary) suffer a failure, the passive device (normally the Secondary) will take over.

14.1.1. Non-Replicated Settings

A number of settings are not replicated as part of the Primary/Secondary pairing process and therefore must be manually configured on the Secondary appliance. These are listed by WebUI menu option in the table below:

WebUI Main Menu Option	Sub Menu Option	Description
Local Configuration	Hostname & DNS	Hostname and DNS settings
Local Configuration	Network Interface Configuration	Interface IP addresses, bonding configuration and VLANs
Local Configuration	Routing	Default gateways and static routes
Local Configuration	System Date & time	Time and date related settings
Local Configuration	Physical – Advanced Configuration	Various appliance settings
Local Configuration	Portal Management	Portal management settings
Local Configuration	Security	Security settings
Local Configuration	SNMP Configuration	SNMP settings
Local Configuration	Graphing	Graphing settings
Local Configuration	License Key	Appliance licensing
Maintenance	Backup & Restore	Local XML backups
Maintenance	Software Updates	Appliance software updates
Maintenance	Firewall Script	Firewall (iptables) configuration
Maintenance	Firewall Lockdown Wizard	Appliance management lockdown settings



① Important

Make sure that where any of the above have been configured on the Primary appliance, they're also configured on the Secondary.


14.1.2. Configuring the HA Clustered Pair

ⓘ Note

If you have already run the firewall lockdown wizard on either appliance, you'll need to ensure that it is temporarily disabled on both appliances whilst performing the pairing process.

1. Deploy a second appliance that will be the Secondary and configure initial network settings.
2. Using the WebUI on the Primary appliance, navigate to: *Cluster Configuration > High-Availability Configuration*.

Create a Clustered Pair



LOADBALANCER

Local IP address
10.11.40.55


IP address of new peer
10.11.40.56

Password for *loadbalancer* user on peer
.....

Add new node

3. Specify the IP address and the *loadbalancer* user's password for the Secondary (peer) appliance as shown in the example above.
4. Click **Add new node**.
5. The pairing process now commences as shown below:

Create a Clustered Pair



LOADBALANCER Primary
IP: 10.11.40.55

Attempting to pair..


LOADBALANCER Secondary
IP: 10.11.40.56

configuring



6. Once complete, the following will be displayed on the Primary appliance:

High Availability Configuration - primary



7. To finalize the configuration, restart heartbeat and any other services as prompted in the "Commit changes" message box at the top of the screen.

Note

Clicking the **Restart Heartbeat** button on the Primary appliance will also automatically restart heartbeat on the Secondary appliance.

Note

For more details on configuring HA with 2 appliances, please refer to [Appliance Clustering for HA](#).

Note

For details on testing and verifying HA, please refer to [Clustered Pair Diagnostics](#).



15. Document Revision History

Version	Date	Change	Reason for Change	Changed By
1.0.0	26 February 2025	Initial version		RJC





Visit us: www.loadbalancer.org

Phone us: +44 (0)330 380 1064

Phone us: +1 833 274 2566

Email us: info@loadbalancer.org

Follow us: [@loadbalancer.org](https://www.loadbalancer.org)

About Loadbalancer.org

Loadbalancer.org's mission is to ensure that its clients' businesses are never interrupted. The load balancer experts ask the right questions to get to the heart of what matters, bringing a depth of understanding to each deployment. Experience enables Loadbalancer.org engineers to design less complex, unbreakable solutions - and to provide exceptional personalized support.

