In-Class Handout Version

15-213

"The Class That Gives CMU Its Zip!"

Bits and Bytes
Aug. 30, 2001

Topics

- Why bits?
- Representing information as bits
  - Binary/Hexadecimal
  - Byte representations
    - » numbers
    - » characters and strings
    - » Instructions
- Bit-level manipulations
  - Boolean algebra
  - Expressing in C

Why Don't Computers Use Base 10?

Base 10 Number Representation

- That's why fingers are known as "digits"
- Natural representation for financial transactions
  - Floating point number cannot exactly represent $1.20
- Even carries through in scientific notation
  - 1.5213×10^4

Implementing Electronically

- Hard to store
  - ENIAC (First electronic computer) used 10 vacuum tubes / digit
- Hard to transmit
  - Need high precision to encode 10 signal levels on single wire
- Messy to implement digital logic functions
  - Addition, multiplication, etc.

Binary Representations

Base 2 Number Representation

- Represent 15213_{10} as 11101101101101_2
- Represent 1.20_{10} as $1.00110011001100 11[0011]\ldots_2$
- Represent 1.5213×10^4 as $1.1101101101101_2 \times 2^{13}$

Electronic Implementation

- Easy to store with bistable elements
- Reliably transmitted on noisy and inaccurate wires



- Straightforward implementation of arithmetic functions

Byte-Oriented Memory Organization

Programs Refer to Virtual Addresses

- Conceptually very large array of bytes
- Actually implemented with hierarchy of different memory types
  - SRAM, DRAM, disk
  - Only allocate for regions actually used by program
- In Unix and Windows NT, address space private to particular "process"
  - Program being executed
  - Program can clobber its own data, but not that of others

Compiler + Run-Time System Control Allocation

- Where different program objects should be stored
- Multiple mechanisms: static, stack, and heap
- In any case, all allocation within single virtual address space

Encoding Byte Values

Byte = 8 bits

- **Binary** 00000000_2 **to** 11111111_2
- **Decimal:** 0_{10} **to** 255_{10}
- **Hexadecimal** 00_{16} **to** FF_{16}
  - **Base 16 number representation**
  - **Use characters '0' to '9' and 'A' to 'F'**
  - **Write $FA1D37B_{16}$ in C as `0xFA1D37B`**
    - » **Or** `0xfa1d37b`

Hex	Decimal	Binary
0	0	0000
1	1	0001
2	2	0010
3	3	0011
4	4	0100
5	5	0101
6	6	0110
7	7	0111
8	8	1000
9	9	1001
A	10	1010
B	11	1011
C	12	1100
D	13	1101
E	14	1110
F	15	1111

Machine Words

Machine Has "Word Size"

- Nominal size of integer-valued data
  - Including addresses
- Most current machines are 32 bits (4 bytes)
  - Limits addresses to 4GB
  - Becoming too small for memory-intensive applications
- High-end systems are 64 bits (8 bytes)
  - Potentially address $\approx$ 1.8 X 10^{19} bytes
- Machines support multiple data formats
  - Fractions or multiples of word size
  - Always integral number of bytes

Word-Oriented Memory Organization

Addresses Specify Byte Locations

- Address of first byte in word
- Addresses of successive words differ by 4 (32-bit) or 8 (64-bit)



Data Representations

Sizes of C Objects (in Bytes)

C Data Type	Compaq Alpha	Typical 32-bit	Intel IA32
`int`	4	4	4
`long int`	8	4	4
`char`	1	1	1
`short`	2	2	2
`float`	4	4	4
`double`	8	8	8
`long double`	8	8	10/12
`char *`	8	4	4

- » Or any other pointer

Byte Ordering

Issue

- How should bytes within multi-byte word be ordered in memory

Conventions

- Alphas, PC's are "Little Endian" machines
  - Least significant byte has lowest address
- Sun's, Mac's are "Big Endian" machines
  - Least significant byte has highest address

Example

- Variable `x` has 4-byte representation `0x01234567`
- Address given by `&x` is `0x100`



Examining Data Representations

Code to Print Byte Representation of Data

- Casting pointer to `unsigned char *` creates byte array

```
typedef unsigned char *pointer;

void show_bytes(pointer start, int len)
{
  int i;
  for (i = 0; i < len; i++)
    printf("0x%p\t0x%.2x\n",
           start+i, start[i]);
  printf("\n");
}
```

Printf directives:

`%p`: Print pointer

`%x`: Print Hexadecimal

`show_bytes` Execution Example

```
int a = 15213;
printf("int a = 15213;\n");
show_bytes((pointer) &a, sizeof(int));
```

Result:

```
int a = 15213;
0x11ffffcb8   0x6d
0x11ffffcb9   0x3b
0x11ffffcba   0x00
0x11ffffcbb   0x00
```

Representing Integers

```
int A = 15213;
int B = -15213;
long int C = 15213;
```

Decimal:	15213
Binary:	0011 1011 0110 1101
Hex:	3 B 6 D

Linux/Alpha A



Sun A

Linux/Alpha B



Sun B

Linux C



Alpha C



Sun C



Two's complement representation
(Covered next lecture)

Representing Pointers

```
int B = -15213;
int *P = &B;
```

Alpha Address

Hex:	1	F	F	F	F	F	C	A	0
Binary:	0001	1111	1111	1111	1111	1111	1100	1010	0000

Alpha P



Sun P



Sun Address

Hex:	E	F	F	F	F	B	2	C
Binary:	1110	1111	1111	1111	1111	1011	0010	1100

Linux Address

Hex:	B	F	F	F	F	8	D	4
Binary:	1011	1111	1111	1111	1111	1000	1101	0100

Linux P



Different compilers & machines assign different locations to objects

Representing Floats

```
Float F = 15213.0;
```



IEEE Single Precision Floating Point Representation

Hex:	4	6	6	D	B	4	0	0
Binary:								
15213:			1110	1101	1011	01		

Not same as integer representation, but consistent across machines

Representing Strings

Strings in C

```
char S[6] = "15213";
```

- Represented by array of characters
- Each character encoded in ASCII format
  - Standard 7-bit encoding of character set
  - Other encodings exist, but uncommon
  - Character "0" has code `0x30`
    - Digit *i* has code `0x30+i`
- String should be null-terminated
  - Final character = 0



Compatibility

- Byte ordering not an issue
  - Data are single byte quantities
- Text files generally platform independent
  - Except for different conventions of line termination character!

Machine-Level Code Representation

Encode Program as Sequence of Instructions

- Each simple operation
  - Arithmetic operation
  - Read or write memory
  - Conditional branch
- Instructions encoded as bytes
  - Alpha's, Sun's, Mac's use 4 byte instructions
    - » Reduced Instruction Set Computer (RISC)
  - PC's use variable length instructions
    - » Complex Instruction Set Computer (CISC)
- Different instruction types and encodings for different machines
  - Most code not binary compatible

Programs are Byte Sequences Too!

Representing Instructions

```
int sum(int x, int y)
{
    return x+y;
}
```

Alpha `sum`

00
00
30
42
01
80
FA
6B

Sun `sum`

81
C3
E0
08
90
02
00
09

PC `sum`

55
89
E5
8B
45
0C
03
45
08
89
EC
5D
C3

- **For this example, Alpha & Sun use two 4-byte instructions**
  - **Use differing numbers of instructions in other cases**
- **PC uses 7 instructions with lengths 1, 2, and 3 bytes**
  - **Same for NT and for Linux**
  - **NT / Linux not fully binary compatible**

Different machines use totally different instructions and encodings

Boolean Algebra

Developed by George Boole in 19th Century

- Algebraic representation of logic
  - Encode "True" as 1 and "False" as 0

And

- A&B = 1 when both A=1 and B=1

&	0	1
0	0	0
1	0	1

Or

- A|B = 1 when either A=1 or B=1

|	0	1
0	0	1
1	1	1

Not

- ~A = 1 when A=0

~	
0	1
1	0

Exclusive-Or (Xor)

- A^B = 1 when either A=1 or B=1, but not both

^	0	1
0	0	1
1	1	0

Application of Boolean Algebra

Applied to Digital Systems by Claude Shannon

- 1937 MIT Master's Thesis
- Reason about networks of relay switches
  - Encode closed switch as 1, open switch as 0



Connection when
A&~B | ~A&B
= A^B

Properties of & and | Operations

Integer Arithmetic

- ⟨Z, +, *, –, 0, 1⟩ **forms a "ring"**
- **Addition is "sum" operation**
- **Multiplication is "product" operation**
- **– is additive inverse**
- **0 is identity for sum**
- **1 is identity for product**

Boolean Algebra

- ⟨{0,1}, |, &, ~, 0, 1⟩ **forms a "Boolean algebra"**
- **Or is "sum" operation**
- **And is "product" operation**
- **~ is "complement" operation (not additive inverse)**
- **0 is identity for sum**
- **1 is identity for product**

Properties of Rings & Boolean Algebras

	Boolean Algebra	Integer Ring
• *Commutativity*		
	A | B = B | A	A + B = B + A
	A & B = B & A	A * B = B * A
• *Associativity*		
	(A | B) | C = A | (B | C)	(A + B) + C = A + (B + C)
	(A & B) & C = A & (B & C)	(A * B) * C = A * (B * C)
• *Product distributes over sum*		
	A & (B | C) = (A & B) | (A & C)	A * (B + C) = A * B + B * C
• *Sum and product identities*		
	A | 0 = A	A + 0 = A
	A & 1 = A	A * 1 = A
• *Zero is product annihilator*		
	A & 0 = 0	A * 0 = 0
• *Cancellation of negation*		
	~ (~ A) = A	– (– A) = A

Ring ≠ Boolean Algebra

Boolean Algebra	Integer Ring
• **Boolean: *Sum distributes over product***	
A | (B & C) = (A | B) & (A | C)	**A + (B * C) ≠ (A + B) * (B + C)**
• **Boolean: *Idempotency***	
A | A = A	**A + A ≠ A**
– **"A is true" or "A is true" = "A is true"**	
A & A = A	**A * A ≠ A**
• **Boolean: *Absorption***	
A | (A & B) = A	**A + (A * B) ≠ A**
– **"A is true" or "A is true and B is true" = "A is true"**	
A & (A | B) = A	**A * (A + B) ≠ A**
• **Boolean: *Laws of Complements***	
A | ~A = 1	**A + –A ≠ 1**
– **"A is true" or "A is false"**	
• **Ring: *Every element has additive inverse***	
A | ~A ≠ 0	**A + –A = 0**

Properties of & and ^

Boolean Ring

- $\langle$**{0,1}, ^, &,** I**, 0, 1**$\rangle$
- **Identical to integers mod 2**
- I **is identity operation:** I **(A) = A**

  A ^ A = 0

Property	Boolean Ring
• Commutative sum	A ^ B = B ^ A
• Commutative product	A & B = B & A
• Associative sum	(A ^ B) ^ C = A ^ (B ^ C)
• Associative product	(A & B) & C = A & (B & C)
• Prod. over sum	A & (B ^ C) = (A & B) ^ (B & C)
• 0 is sum identity	A ^ 0 = A
• 1 is prod. identity	A & 1 = A
• 0 is product annihilator	A & 0 = 0
• Additive inverse	A ^ A = 0

Relations Between Operations

DeMorgan's Laws

- Express & in terms of |, and vice-versa

  A & B = ~(~A | ~B)

  » A and B are true if and only if neither A nor B is false

  A | B = ~(~A & ~B)

  » A or B are true if and only if A and B are not both false

Exclusive-Or using Inclusive Or

A ^ B = (~A & B) | (A & ~B)

» Exactly one of A and B is true

A ^ B = (A | B) & ~(A & B)

» Either A is true, or B is true, but not both

General Boolean Algebras

Operate on Bit Vectors

- **Operations applied bitwise**

```
  01101001      01101001      01101001
& 01010101    | 01010101    ^ 01010101    ~ 01010101
```

Representation of Sets

- **Width *w* bit vector represents subsets of** {0, …, *w*–1}
- $a_j = 1$ **if** $j \in A$
  - **01101001** { }
  - **01010101** { }



- **&** **Intersection** **01000001**
- **|** **Union** **01111101**
- **^** **Symmetric difference** **00111100**
- **~** **Complement** **10101010**

Bit-Level Operations in C

Operations &, |, ~, ^ Available in C

- Apply to any "integral" data type
  - `long, int, short, char`
- View arguments as bit vectors
- Arguments applied bit-wise

Examples (Char data type)

- `~0x41 -->`
  $\sim 01000001_2 \rightarrow 10111110_2$
- `~0x00 -->`
  $\sim 00000000_2 \rightarrow 11111111_2$

- `0x69 & 0x55 -->`
  $01101001_2 \;\&\; 01010101_2 \rightarrow 01000001_2$
- `0x69 | 0x55 -->`
  $01101001_2 \;|\; 01010101_2 \rightarrow 01111101_2$

Contrast: Logic Operations in C

Contrast to Logical Operators

- `&&, ||, !`
  - View 0 as "False"
  - Anything nonzero as "True"
  - Always return 0 or 1
  - Early termination

Examples (char data type)

- `!0x41  -->`
- `!0x00  -->`
- `!!0x41 -->`



- `0x69 && 0x55  -->`
- `0x69 || 0x55  -->`



- `p && *p` (avoids null pointer access)

Shift Operations

Left Shift: `x << y`

- Shift bit-vector `x` left `y` positions
  - Throw away extra bits on left
  - Fill with 0's on right

Right Shift: `x >> y`

- Shift bit-vector `x` right `y` positions
  - Throw away extra bits on right
- Logical shift
  - Fill with 0's on left
- Arithmetic shift
  - Replicate most significant bit on right
  - Useful with two's complement integer representation

Argument x	01100010
<< 3	
Log. >> 2	
Arith. >> 2	

Argument x	10100010
<< 3	
Log. >> 2	
Arith. >> 2	

Cool Stuff with Xor

- **Bitwise Xor is form of addition**
- **With extra property that every value is its own additive inverse**

  A ^ A = 0

```
void funny(int *x, int *y)
{
    *x = *x ^ *y;      /* #1 */
    *y = *x ^ *y;      /* #2 */
    *x = *x ^ *y;      /* #3 */
}
```

Step	*x	*y
Begin	A	B
1	A^B	B
2		
3		
End		