

# Reduced Row Echelon Form

Young W Lim

Nov 11, 2024

Copyright (c) 2024 Young W. Lim.

Permission is granted to copy, distribute and/or modify this document under the terms of the GNU Free Documentation License, Version 1.2 or any later version published by the Free Software Foundation; with no Invariant Sections, no Front-Cover Texts, and no Back-Cover Texts.

This work is licensed under a Creative Commons  
"Attribution-NonCommercial-ShareAlike 3.0 Unported"  
license.



Based on

A First Course in Linear Algebra, R. A. Beezer

<http://linear.ups.edu/fcla/front-matter.html>

# Outline

- 1 Reduced Row Echelon Form
  - Reduced Row Echelon Form

# Outline

- 1 Reduced Row Echelon Form
  - Reduced Row Echelon Form

# Matrix (1)

## Matrix

An  $m \times n$  matrix is  
a rectangular layout of numbers from  $C$   
having  $m$  rows and  $n$  columns.

- Rows of a matrix will be referenced starting at the top and working down (i.e. row 1 is at the top)
- columns will be referenced starting from the left (i.e. column 1 is at the left).

# Matrix (2)

## Matrix

- use upper-case Latin letters from the start of the alphabet (A,B,C,...) to denote matrices and
- squared-off brackets to delimit the layout.
- For a matrix  $A$ , the notation  $[A]_{ij}$  will refer to the complex number in row  $i$  and column  $j$  of  $A$ .

# Column Vector

## Column Vector

A column vector of size  $m$  is an ordered list of  $m$  numbers, which is written in order vertically, starting at the top and proceeding to the bottom.

- Column vectors will be written in bold, usually with lower case Latin letter from the end of the alphabet such as  $u, v, w, x, y, z$ .
- Some books like to write vectors with arrows, such as  $\vec{u}$ .
- Writing by hand, some like to put arrows on top of the symbol, or a tilde underneath the symbol, as in  $\tilde{v}$ .
- To refer to the entry or component of vector  $v$  in location  $i$  of the list, we write  $[v]_i$ .

# Zero Column Vector

## Zero Column Vector

The zero vector of size  $m$  is the column vector of size  $m$  where each entry is the number zero,

$$0 = \begin{bmatrix} 0 \\ 0 \\ 0 \\ 0 \\ \vdots \\ 0 \end{bmatrix}$$

or defined much more compactly,  $[0]_i=0$  for  $1 \leq i \leq m$ .



# Coefficient Matrix

## Coefficient Matrix

For a system of linear equations,

$$\begin{array}{rcl}
 a_{11}x_1 + a_{12}x_2 + a_{13}x_3 + \cdots + a_{1n}x_n & = & b_1 \\
 a_{21}x_1 + a_{22}x_2 + a_{23}x_3 + \cdots + a_{2n}x_n & = & b_2 \\
 a_{31}x_1 + a_{32}x_2 + a_{33}x_3 + \cdots + a_{3n}x_n & = & b_3 \\
 \vdots & & \vdots \\
 a_{m1}x_1 + a_{m2}x_2 + a_{m3}x_3 + \cdots + a_{mn}x_n & = & b_m
 \end{array}$$

the coefficient matrix is the  $m \times n$  matrix

$$\begin{bmatrix}
 a_{11} & a_{12} & a_{13} & \cdots & a_{1n} \\
 a_{21} & a_{22} & a_{23} & \cdots & a_{2n} \\
 a_{31} & a_{32} & a_{33} & \cdots & a_{3n} \\
 \vdots & \vdots & \vdots & \ddots & \vdots \\
 a_{m1} & a_{m2} & a_{m3} & \cdots & a_{mn}
 \end{bmatrix}$$

# Vector of Constants

## Vector of Constants

For a system of linear equations,

$$\begin{array}{rcl} a_{11}x_1 + a_{12}x_2 + a_{13}x_3 + \cdots + a_{1n}x_n & = & b_1 \\ a_{21}x_1 + a_{22}x_2 + a_{23}x_3 + \cdots + a_{2n}x_n & = & b_2 \\ a_{31}x_1 + a_{32}x_2 + a_{33}x_3 + \cdots + a_{3n}x_n & = & b_3 \\ & \vdots & \\ a_{m1}x_1 + a_{m2}x_2 + a_{m3}x_3 + \cdots + a_{mn}x_n & = & b_m \end{array}$$

the vector of constants is the column vector of size  $m$

$$\mathbf{b} = \begin{bmatrix} b_1 \\ b_2 \\ b_3 \\ \vdots \\ b_m \end{bmatrix}$$

# Solution Vector

## Solution Vector

For a system of linear equations,

$$\begin{aligned}a_{11}x_1 + a_{12}x_2 + a_{13}x_3 + \cdots + a_{1n}x_n &= b_1 \\a_{21}x_1 + a_{22}x_2 + a_{23}x_3 + \cdots + a_{2n}x_n &= b_2 \\a_{31}x_1 + a_{32}x_2 + a_{33}x_3 + \cdots + a_{3n}x_n &= b_3 \\&\vdots \\a_{m1}x_1 + a_{m2}x_2 + a_{m3}x_3 + \cdots + a_{mn}x_n &= b_m\end{aligned}$$

the solution vector is the column vector of size  $n$

$$\mathbf{x} = \begin{bmatrix} x_1 \\ x_2 \\ x_3 \\ \vdots \\ x_n \end{bmatrix}$$

# Matrix Representation of a Linear System

## Matrix Representation

If  $\mathbf{A}$  is the coefficient matrix of a system of linear equations and  $\mathbf{b}$  is the vector of constants, then we will write  $LS(\mathbf{A}, \mathbf{b})$  as a shorthand expression for the system of linear equations, which we will refer to as the matrix representation of the linear system.

# Augmented Matrix

## Augmented Matrix

Suppose we have a system of  $m$  equations in  $n$  variables, with coefficient matrix  $A$  and vector of constants  $b$ .

Then the augmented matrix of the system of equations is the  $m \times (n+1)$  matrix whose first  $n$  columns are the columns of  $A$  and whose last column ( $n+1$ ) is the column vector  $b$ .

When described symbolically, this matrix will be written as  $[A|b]$ .

# Augmented Matrix Example

## Augmented Matrix Example

Archetype A is the following system of 3 equations in 3 variables.

$$\begin{array}{rclcrcl} x_1 & -x_2 & +2x_3 & = & 1 \\ 2x_1 & +x_2 & +x_3 & = & 8 \\ x_1 & +x_2 & & = & 5 \end{array}$$

Here is its augmented matrix.

$$\left[ \begin{array}{cccc} 1 & -1 & 2 & 1 \\ 2 & 1 & 1 & 8 \\ 1 & 1 & 0 & 5 \end{array} \right]$$

# Row Operations

## Augmented Matrix Example

The following three operations will transform an  $m \times n$  matrix into a different matrix of the same size, and each is known as a row operation.

- 1  $R_i \leftrightarrow R_j$ : Swap the location of rows  $i$  and  $j$
- 2  $\alpha R_i$ : Multiply row  $i$  by the nonzero scalar  $\alpha$
- 3  $\alpha R_i + R_j$ : Multiply row  $i$  by the scalar  $\alpha$  and add to row  $j$

# Row Equivalent Matrices

## Row Equivalent Matrices

Two matrices,  $A$  and  $B$ , are row-equivalent if one can be obtained from the other by a sequence of **row operations**.



# Two Row Equivalent Matrices

## Row Equivalent Matrix Example

The matrices

$$A = \begin{bmatrix} 2 & -1 & 3 & 4 \\ 5 & 2 & -2 & 3 \\ 1 & 1 & 0 & 6 \end{bmatrix}$$

$$B = \begin{bmatrix} 1 & 1 & 0 & 6 \\ 3 & 0 & -2 & -9 \\ 2 & -1 & 3 & 4 \end{bmatrix}$$

are row equivalent

$$\begin{bmatrix} 2 & -1 & 3 & 4 \\ 5 & 2 & -2 & 3 \\ 1 & 1 & 0 & 6 \end{bmatrix} : R_1 \leftrightarrow R_3 \Rightarrow \begin{bmatrix} 1 & 1 & 0 & 6 \\ 5 & 2 & -2 & 3 \\ 2 & -1 & 3 & 4 \end{bmatrix}$$

$$\begin{bmatrix} 1 & 1 & 0 & 6 \\ 5 & 2 & -2 & 3 \\ 2 & -1 & 3 & 4 \end{bmatrix} : -2R_1 + R_2 \Rightarrow \begin{bmatrix} 1 & 1 & 0 & 6 \\ 3 & 0 & -2 & -9 \\ 2 & -1 & 3 & 4 \end{bmatrix}$$

# Row Equivalent Matrices

## Equivalent Systems

Suppose that  $A$  and  $B$  are row-equivalent augmented matrices.

Then the two systems of linear equations represented by  $A$  and  $B$  are equivalent systems

# Reduced Row-Echelon Form

## Reduced Row-Echelon Form

A matrix is in reduced row-echelon form if it meets all of the following conditions:

- 1 If there is a row where every entry is zero, then this row lies below any other row that contains a nonzero entry.
- 2 The leftmost nonzero entry of a row is equal to 1.
- 3 The leftmost nonzero entry of a row is the only nonzero entry in its column.
- 4 Consider any two different leftmost nonzero entries, one located in row  $i$ , column  $j$  and the other located in row  $s$ , column  $t$ . If  $s > i$ , then  $t > j$

